



# Compact 3-in-1 mono laser printer

**DCP-1612W** 









## Compact 3-in-1 mono laser printer

A great choice for the home or small office with print, copy and scan functionality, all in one compact device. The DCP-1612W is easy to set up and use, offering great features at an affordable price.

**DCP-1612W** 



### **Key features:**

- Wireless and mobile connectivity
- 150 sheet paper input
- 20 pages per minute print speed (ppm)
- Compact size.



#### Professional print bundle that works from home

#### **Compact and desktop friendly**

The DCP-1612W is a solid all-rounder providing print, copy and scan functionality in one compact device. Whether for home or small office use, you can put the DCP-1612W wherever it's most convenient for you.

#### Built with convenience in mind

Gone are the days of needing endless wires to connect to your printer. With the DCP-1612W anyone can connect quickly and easily via wireless connection, or alternatively print direct from a mobile or tablet device; you don't even need to turn on a computer.



<sup>\*</sup> The predicted savings are based on usage of 130 pages per month over a 36 month period. The estimated yield of each toner cartridge is calculated using ISO/IEC19752. Brother printer pricing used Brother's suggested retail prices. Competitor's printer pricing was based on pricing from Context [Mono laser multifunction devices] which sets out the top 20 best-selling mono laser printers in [April 2019 to March 2020] in the UK). Supplies pricing was based on pricing from Gfk's [PanelMarkt report, mono laser consumables] which sets out the average selling prices for standard yield toners in the UK for [April 2019 to March 2020]

#### General

**Technology** 

Electrophotographic laser

**Processor** ARM9 200Mhz **Wireless network** IEEE 802.11b/g/n

**Control panel** 2 line LCD

Memory 32MB Local interface

Hi-speed USB 2.0

Mobile print

Print from your mobile devices to your Brother printer

**Warranty**2 year warranty

#### **Print**

Print speed (A4)

20ppm printing speed

Resolution 2,400 x 600dpi (HQ1200 technology) First print out time

Less than 10 seconds from ready mode

Warm up time

Less than 18 seconds from sleep mode

**Print languages**GDI

#### **Printer functions**

N-up printing<sup>3</sup>

Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16) Poster printing<sup>4</sup>

Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages

Watermark printing<sup>4</sup>

Watermark your documents with predefined text or with your own user-defined messages

Manual 2-sided print<sup>4</sup>

Manual 2-sided printing (recommended for media not supported by automatic 2-sided print)

#### **Printer drivers**

Windows

Windows XP Home and Professional, Vista, 7, 8, 8.1 Windows Server 2012, 2012R2, 2008, 2008 R2, 2003, 2003 x64 Edition Macintosh<sup>5</sup>

OS X v10.7.5, 10.8.x, 10.9.x

Linux<sup>5</sup>

CUPS, LPD/LPRng (x86/x64 environment)

\*Windows Server supports network printing only

<sup>1</sup> Approx declared vield value in accordance with ISO/IEC 19798.

<sup>2</sup> Calculated with 80g/m² paper.

<sup>3</sup> Windows and Mac® only.

<sup>4</sup> Windows only.

<sup>5</sup> Optional download.

<sup>6</sup> Optional download.
6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products.
For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

#### Paper handling

#### Paper input

Standard tray - 150 sheets

#### Paper output

50 sheets face down (80g/m2)

#### Media sizes Standard tray

A4, letter, legal, folio, A5, A5 (long edge), B5, executive

## Media type and weights Standard tray

Plain and recycled paper (between 65 - 105g/m2)

## Mobile and web connectivity

## Brother iPrint&Scan (Android)

Print from, scan to, preview copies and check the machine status from an Android device

## Brother iPrint&Scan (iPad / iPhone / iPod)

Print from, scan to, preview copies and check the machine status from an iPad / iPhone / iPod Touch

## Brother iPrint&Scan (Windows Phone)

Print from and scan to a smart phone running the Windows Phone operating system

## Brother iPrint&Scan (Windows 8,10 and RT)

Print from and scan to a Windows 8,10 or Windows RT tablet

## **Brother print service plugin**Print from Android devices without a dedicated app

#### Copy

#### Print speed (A4)

20 mono copies per minute copying speed

#### First copy out time

Less than 16 seconds from ready mode (mono)

#### Resolution

600 x 600dpi

#### Multi-copying/stack/sort

Makes up to 99 copies of each page/stacks or sorts

### Enlargement / reduction ratio

Reduce or increase document sizes from 25% to 400% in 1% increments

#### N in 1 copying

Allows the user to compress 2 or 4 pages on to a single A4 sheet

#### 2-in-1 ID copying

Allows the user to copy both sides of an ID card to a single A4 sheet

#### Greyscale

256 shades of grey (8 bit)

<sup>1</sup> Approx declared vield value in accordance with ISO/IEC 19798.

<sup>2</sup> Calculated with 80g/m² paper.

<sup>3</sup> Windows and Mac® only.

<sup>4</sup> Windows only.

<sup>5</sup> Optional download.

<sup>6</sup> Optional download.
6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products.
For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

#### Scan

#### Scanner type

Contact image sensor

#### Colour and mono scanning

Yes

#### Scan speed mono

4.23 images per minute mono scanning speed 7.42 images per minute colour scanning speed

## Scan resolution from scanner glass

600 x 1,200dpi

## Interpolated scan resolution

19,200 x 19,200dpi

#### Colour depth

48 bit color processing (input) 24 bit color processing (output)

#### Greyscale

16 bit color processing (input) 8 bit color processing (output)

#### Scanner functions

#### Scan to e-mail

Scan and share documents via e-mail server

#### Scan to image

Scan into your preferred image editing software

#### Scan to file

Scan to a file on your computer

#### Base colour removal

Yes

#### ID scan

Yes

#### 1 to 2 scan

Yes

#### **Scanner drivers**

#### Windows

TWAIN and WIA XP Vista Windows 7 Windows 8

Windows 8.1

#### Macintosh<sup>5</sup>

TWAIN/ICA

#### Linux<sup>5</sup>

SANE (32 and 64 bit editions)

## Fleet management tools

#### Unattended installer4

Ability to centrally deploy and customise our drivers and software

#### MSI installer4

Modular installers that can be distributed through Active Directory®

#### **BRAdmin Light**<sup>4&5</sup>

LAN/WAN management software

#### Embedded web server

Web based print management software embedded onto the device

#### **Driver Deployment Wizard**<sup>4&5</sup>

Easily create print drivers for hassle free deployment over your network

#### **PrintSmart Cost Control**

Monitor and control printing costs for all Brother and 3rd party devices.

For more information on PrintSmart solutions visit: brother.co.uk

<sup>1</sup> Approx declared yield value in accordance with ISO/IEC 19798.

<sup>2</sup> Calculated with 80g/m² paper.

<sup>3</sup> Windows and Mac® only.

<sup>4</sup> Windows only.

<sup>5</sup> Optional download.

<sup>6</sup> Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

#### **Network and security**

#### Wireless network

IIEEE 802.11b/g/n (infrastructure mode/ ad-hoc mode)

#### Wireless network security

WEP 64/128, WPA-PSK (TKIP/ AES), WPA2-PSK (AES), SMTP-AUTH

#### Wi-Fi Direct™

Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported)

## Wireless setup support WPS. AOSS

## **Wireless applications**Vertical pairing

#### IPv4

ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/ Port 9100, IPP, FTP Server, SNMPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client, ICMP, Web Services (Print)

#### IPv6

NDP, RA, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/ Port 9100, IPP, FTP Server, SN-MPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client, ICMPv6, Web Services (Print)

#### IP filter

Restrict which network users can or cannot access the device over the network (IPv4 only)

#### **E-mail notifications**

Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

## Supplies and accessories

#### In-box toner<sup>1</sup>

700 pages black (in accordance with ISO/IEC 19752)

#### Standard yield toner<sup>1</sup>

1,000 pages black (in accordance with ISO/IEC 19752)

#### Drum unit<sup>1</sup>

10,000 pages (1 page/job) (DR-1050)

<sup>1</sup> Approx declared yield value in accordance with ISO/IEC 19798.

<sup>2</sup> Calculated with 80g/m² paper.

<sup>3</sup> Windows and Mac® only.

<sup>4</sup> Windows only.

<sup>5</sup> Optional download.

<sup>6</sup> Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

#### **Duty cycles**

#### **Recommended monthly**

250 to 1,800 pages monthly print volume

#### Maximum monthly<sup>6</sup>

Up to 10,000 pages monthly print volume

#### **Environment**

#### **Power consumption**

Printing - 390w Ready - 50w Deep sleep - 0.9w

**TEC** value

0.7 kWh/week

Sound pressure level

Printing - 52dB(A) Ready - 32dB(A)

Sound power

Printing - 6.6dB(A) Ready - 4.7dB(A) Deep sleep - inaudible

#### **Power saving**

This enables the printer to consume less energy when not in use

#### **Toner saving**

This reduces the toner usage and helps to reduce the total cost of printer ownership

<sup>1</sup> Approx declared yield value in accordance with ISO/IEC 19798.

<sup>2</sup> Calculated with 80g/m² paper.

<sup>3</sup> Windows and Mac® only. 4 Windows only. 5 Optional download.

<sup>6</sup> Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.





#### Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.

www.brotherearth.com

